

ST278

● Features

- Combines two pairs of high output GaAs IREDS with high sensitive phototransistors.
- Moving direction can be detected.
- Wide detecting range, minimum range is 2mm.
- Non-contact detecting manner
- Applications
- IC card electric power meter
- AMR system
- Water meter
- OA equipment: facsimile, printer, copier etc
- Combined with direction detector IC(ST288A), it can be used as detecting moving abject direction, speed of clockwise/ counterclockwise rotation and moving distance etc.

● Absolute Maximum Ratings($T_a=25^{\circ}\text{C}$)

Parameter		Symbol	Rating	Unit
Input	Forward Current	I _F	50	mV
	Reverse Voltage	V _R	6	V
	Power Dissipation	P	75	mW
Output	Collector-Emitter Voltage	V _{C EO}	25	V
	Emitter-Collector Voltage	V _{E CO}	6	V
	Collector Power Dissipation	P _C	50	mW
*Operating Temperature		T _{opr}	-20~65	°C
Storage Temperature		T _{stg}	-30~75	°C
** Soldering Temperature		T _{sol}	260	°C

*The special requirement could be met according to customer's request.

**Soldering time: 5s max. Soldering position: at least 1.5mm from the base of the package.

● Electro-Optical Characteristics($T_a=25^{\circ}\text{C}$)

Parameter		Symbol	Condition	Min.	Typ.	Max.	Unit	
Input	Forward Voltage	V _F	I _F =20mA		-	1.25	1.5	V
	Reverse Current	I _R	V _R =3V		-	-	10	μ A
Output	Collector Dark Current	I _{C EO}	V _{C E} =20V		-	-	1.0	μ A
	Collector Light Current		V _{C E} =5V I _F =8mA	L3	0.3	-	-	mA
				L4	0.4	-	-	mA
				L5	0.5	-	-	mA
	Collector Current Ratio	I _{c1} /I _{c2}	V _{C E} =15V I _F =8mA		0.71	-	1.4	-
Transfer Character-istics	Collector-Emitter Saturation Voltage		I _F =8mA I _c =0.15mA		-	-	0.4	V
	Response Time	Rise Time	Tr	I _F =20mA		10	-	μ S
		Fall Time	T _f	V _{C E} =5V R _c =100		-	10	μ S

Notes: Collector light current I_L, Collector-emitter saturation voltage V_{C E(SAT)}, Relative current , Response time is measured within 2~5mm between photointerrupter's top and reflecting surface. The value is affected by the smooth of light reflecting surface.

